

I. Melodka – Lights

1) Control system:

Daslight Virtual Controller DVC4 + GZM interface + 21" Touchscreen (AiO PC) + 3x Novation MIDI controller

Used DMX universes: 3

Used DMX channels: 762

Connectors: 3-pin XLR

2) Fixtures:

Total number of fixtures: 96

32x Flash 18x3 RGB LED Mini Beam-Wash Moving Head

4x Flash 7x15 Osram RGBW Big LED Eye Kaleidoscope Moving Head

10x Flash 8x10 White LED Move Washer (Moving Sunstrip)

3x Flash LED PAR 64 300W 6in1 COB RGBWA UV + BARNDOOR

6x Flash LED PIXEL 30W RGBW 4in1 COB SPOT ZOOM 15-120° (small Fresnell)

32x PAR 36 (halogen)

6x PAR 56 (halogen)

2x 2-eye Blinder (halogen)

1x Haze Base Classic 1300 W Fog machine/hazer

All fixtures (except fog machine) are hanged on truss.

If you want to use our lighting system with another console or another fixtures, it is generally possible, but for seamless job please read following notes:

- 1) We can't provide you with another equipment, than written above.
- 2) We can't move or remove our fixtures on the truss, change DMX universes, change DMX addresses or DMX modes.
- 3) Our trussing is fully occupied and there's nearly no free place for another equipment. If you want to use your own fixtures, it probably must be placed somewhere else (on the floor, mobile stands etc.)
- 4) We are using DMX connectors in 3-pin XLR format. If you need anything else, please bring your own appropriate adapters.
- 5) Your console or SW must be able to controll at least 3 DMX Universes

- 6) We can't provide you with another fixtures personality files than in *.SSL2 format.

If your console or SW uses another personality file than *.SSL2, there are following options:

- a) Ask producer of your console to provide you by appropriate personality files for our fixtures. (All are made by Flash-Butrym – Poland)
- b) You can use personality file of another product with similar channel layout.
- c) You can create your own personality files, if you know, how to do that:)

To help you with c), here are some useful info about our fixtures:

1) Flash 18x3 RGB LED Mini Beam-Wash Moving Head

Total 32 pcs
Placed in 8x4 Matrix layout on back trusses 1 - 4
12 DMX channel mode
Universe: 3
Channels: 1 – 384
Channels:
1 – Pan
2 – u-Pan
3 – Tilt
4 – u-Tilt
5 – Dimmer
6 – R
7 – G
8 – B
9 – Macro color
10 – Shutter/Strobo
11 – Macro
12 – Macro

2) Flash Big LED Eye Kaleidoscope 7x15 Osram RGBW Moving Head

Total 4 pcs
Placed on back truss 3 In Line
25 DMX channel mode
Universe: 3
Channels: 385 - 484
Channels:
1 – R
2 – G
3 – B
4 – W
5 – CTO
6 – Macro color
7 – Shutter
8 – Master Dimmer

- 9 – Pan
- 10 – Tilt
- 11 – Function
- 12 – Reset
- 13 – Zoom
- 14 – Zoom Rotation
- 15 – Shape selection (LED GoBo)
- 16 – Shape Speed
- 17 – Shape fade
- 18 – Shape R
- 19 – Shape G
- 20 – Shape B
- 21 – Shape W
- 22 – Shape Dimmer
- 23 – Background Dimmer
- 24 – Shape transition
- 25 – Shape offset

3) Flash 8x10 White LED Move Washer (Moving Sunstrip)

- Total 10 pcs
- Square layout on back truss 1 - 4
- 14 DMX channel mode
- Universe: 2
- Channels: 101 - 240
- Channels:
 - 1 – Tilt
 - 2 – Tilt speed
 - 3 – Dimmer
 - 4 – Shutter
 - 5 – Macro
 - 6 – Macro speed (special)
 - 7 – Dim Pixel 1
 - 8 – Dim Pixel 2
 - 9 – Dim Pixel 3
 - 10 – Dim Pixel 4
 - 11 – Dim Pixel 5
 - 12 – Dim Pixel 6
 - 13 – Dim Pixel 7
 - 14 – Dim Pixel 8

4) Flash LED PAR 64 300W 6in1 COB RGBWA UV + BARNDOOR

- Total 3 pcs
- In Line layout over the front of the stage
- 10 DMX channel mode
- Universe: 2
- Channels: 65 - 94
- Channels:
 - 1 – Dimmer
 - 2 – Strobe
 - 3 – R
 - 4 – G
 - 5 – B

- 6 – W
- 7 – A
- 8 – UV
- 9 – Macro color
- 10 – Macro speed

5) Flash LED PIXEL 30W RGBW 4in1 COB SPOT ZOOM 15-120°

- Total 6 pcs
- Front truss (4 pcs) + Mid truss (2 pcs)
- 6 DMX channel mode
- Universe: 1 (front) + 2 (mid)
- Channels: 1 – 24 (front U1) + 1 – 12 (mid U2)
- Channels:
- 1 – Dimmer
- 2 – R
- 3 – G
- 4 – B
- 5 – W
- 6 – Shutter + special

6) PAR 36

- Total 32 pcs
- Placed in 8x4 Matrix layout on back trusses 1 - 4
- 1 DMX channel mode
- Universe: 2
- Channels: 43 - 74
- Channels:
- 1 – Dimmer

7) 2-eye Blinder/PAR56

- Total 5 pcs
- Placed In Line on front and Mid truss
- 1 DMX channel mode
- Universe: 2
- Channels: 27- 31
- Channels:
- 1 – Dimmer

8) Haze Base Classic 1300 W Fog machine/hazer

- Placed behind the right side of the drum riser
- 1 DMX channel mode
- Universe: 3
- Channels: 507
- Channels:
- 1 – Fog

